Connection	Power Rail		Connection	Receiver / Power Rail		Connection	Receiver / Power Rail		Connection	Receiver / Power Rail		Connection	Receiver / Power Rail	
CN24 / CN25	D12.0V	p24	L1	SATA connector	p9									
			direct	BACKLIGHT connector	p17									
			R449 (NM)	INIC CN connector	p21									
			RLED	LEDs	p24									
			direct	IO Board connector	p24									
			R531	CPU FAN connector	p24									
			U35 + IC1 + **R485**	VSYS	p24	U37 + **R601**	D1.0V	p25	direct	U1 VDD	p5, 6			
									direct	U1 VDDD_SATA1	p5, 6			
									direct	U1 VDDD_SATA0	p5, 6			
						U37 + **R602**	D3.3V	p25	direct	U1 Audio clock from oscillator	p2			
									direct	U1 VD331	p5, 6			
									direct	U1 VCCQ	p5, 6			
									R71	U1 VCCQ33_MLBP	p5, 6			
									R74	U1 VCCQ_SD3	p5, 6			
									R76	U1 VCCQ_SD1	p5, 6			
									direct	U6 clock driver	p9			
									direct	U11 System Reset controller & LED	p12			
									direct	2x SPI Flash VCC	p13			
									direct	External Memory connector	p13			
									direct	eMMC VCC	p14			
									direct	U21 Ethernet controller + LED	p15			
									L14	U21 Ethernet VDDA3.3V (D3.3V filtered)	p15			
									direct	U24 HDMI Output tranceiver VCC	p16			
									direct	U23 HDMI Transmitter clock oscillator	p16			
									direct	HDMI Output Hotplug LED	p16			
									direct	U22 HDMI Output LVDS Receiver VCC	p16			
									direct	U30 Video Decoder DVDDIO	p20			
									direct	INIC CN connector	p21			
									direct	U31 Audio device oscillator	p21			
									direct	General Purpose LEDs	p22			
									direct	U35 Power controller	p24			
									direct	IO Board connector	p24			
									direct	Glu VCC	p11, 12, 22			
									direct	Pull-ups	p2, 3, 10, 11, 12, 13, 14, 15, 16, 17, 21, 22, 24, 25			
									L25	V3.3V	p17	direct	U25 D/A Converter	p17
									R398	DVDD_D3.3V	p18	direct	U29 HDMI Input Tranceiver	p18, 19
									L26	TVDD_A3.3V	p18	direct	U29 HDMI Input Tranceiver	p18, 19
									L31	AUDIO_3.3V	p21	direct	U31 Audio device	p21
						U37 + **R603**	D1.8V	p25	direct	U1 CLKIN0, 1 & 2 from oscillator	p2			
									direct	U1 EXTAL from oscillator	p3			
									R32 & R34	ARM_EML connector	p3			
									direct	U1 DDR MSTB_VREF	p4			
									direct	U1 VCCQ18	p5, 6			
									L54	U1 VDDA_SATA1	p5, 6			
									L55	U1 VDDA_SATA0	p5, 6			
									R68	U1 VCCQ18_MLBP	p5, 6			
									R80	U1 VDDQ_LVDS	p5, 6			
									direct	U1 VD181	p5, 6			
									L48	U1 AVDD	p5, 6			
									R65	U1 VDD_CPGPLL0	p5, 6			
									R66	U1 VDD_CPGPLL1	p5, 6			
									R64	U1 VDD_CPGPLL2	p5, 6			
									R69	U1 VDD_CPGPLL3	p5, 6			
									R72	U1 DU_LVDS0_PLL1_VCC	p5, 6			
									R78	U1 DU_LVDS1_PLL1_VCC	p5, 6			
									R81	U1 VDD_MLBPLL	p5, 6			
									R83	U1 VDD_MLBPLL0	p5, 6			
									R86	U1 VDD_MLBPLL1	p5, 6			
									R95	U1 VDDQ_M1BKUP	p5, 6			
									direct	U1 VDDQ_M1A	p5, 6			
									R63	U1 VDDQ_M0APLL	p5, 6			
									R67	U1 VDDQ_M0DPLL0	p5, 6			
									R70	U1 VDDQ_M0DPLL1	p5, 6			
									R73	U1 VDDQ_M0DPLL2	p5, 6			
									R79	U1 VDDQ_M0DPLL3	p5, 6			
									R84	U1 VDDQ_M1APLL	p5, 6			
									R87	U1 VDDQ_M1MPLL	p5, 6			
									R88	U1 VDDQ_M1DPLL0	p5, 6			
									R94	U1 VDDQ_M1DPLL1	p5, 6			
									R97	U1 VDDQ_M1DPLL2	p5, 6			
									R104	U1 VDDQ_M1DPLL3	p5, 6			
									direct	Glu VCC	p3			
									direct	Pull-ups	p3, 4			
						U37 + **L41**	D1.8V_PERI	p25	JP3	SDCard connector channel 0 VDD	p14			
									L16	U23 HDMI Output Transmitter AVDD_18	p16			
									L18	U23 HDMI Output Transmitter DVDD_18	p16			
									L20	U23 HDMI Output Transmitter PLVDD_18	p16			
									L29	U30 Video Decoder AVDD	p20			
									L30	U30 Video Decoder VDEC1_PVDD	p20			
									direct	U30 Video Decoder DVDD	p20			
									direct	U30 Video Decoder XTAL from oscillator	p20			
									R399	DVDD_D1.8V	p18	direct	U29 HDMI Input Tranceiver	p18, 19
									L27	CVDD_A1.8V	p18	direct	U29 HDMI Input Tranceiver	p18, 19
									L28	PVDD_A1.8V	p18	direct	U29 HDMI Input Tranceiver	p18, 19
						U37	VLDO1_IO	p25						
							VCCQ1.8V	p25	direct	U1 VCCQ_ISO	p5			
							VLDO3_SD0	p25	R89	VCCQ_SD0	p25	R77	U1 VCCQ_SD0	p5
												direct	Pull-ups	p14
							VLDO4_SD2	p25	R101	VCCQ_SD2	p25	R75	U1 VCCQ_SD2	p5
												direct	Pull-ups	p14
							VIO33	p25	direct	U37 PMIC VDD_IO2	p25			
									direct	Pull-ups	p25			
							VLDO6_IO	p25						
							VLDO7_1.8V	p25	direct	U38 PMIC VDD_IO	p25			
									direct	U37 PMIC VDD_IO1	p25			
									direct	Pull-ups	p25			
							VLDO8_IO	p25						
							VLDO9_IO	p25						
							VLDO10_IO	p25						
							VLDO11_IO	p25						
							VDDCORE	p25	direct	Pull-ups	p25			
			U35 + IC2 + **R500**	D5.0V	p24	L2	SATA connector	p9						
						U7 + L6	USB3 VBUS	p10						
						U8 + L9	USB2-A VBUS	p11						
						U9 + L12	USB2-miniAB VBUS	p11						
						direct	U24 HDMI Output VCC	p16						
						TR5	HDMI-A hotplug-det	p19						
						RLED	HDMI-A hotplug-det LED	p19						
						direct	IO Board connector	p24						
						R534	CPU FAN connector	p24						
						direct	Glu VCC	p17						
						U28	LVDS_MON_POWER	p17	direct	LCD Display connector	p17			
						U39	SDIF_POWER	p14	U18 + **JP3**	SDCard connector channel 0 VDD	p14			
									U19	sDCard connector channel 2 VDD	p14			
						U38 + **R584**	DVFS1.0V	p25	direct	U1 VDD_DVFS	p5, 6			
						U36	VTT	p24	direct	DDR bus termination resistors	p8			
						U36 + IC3 + **R585**	D1.5V	p24	direct	U1 DDR VREF	p4			
									R93	U1 VDDQ_M0BKUP	p5, 6			
									direct	U1 VDDQ_M0	p5, 6			
									direct	U1 VDDQ_M1	p5, 6			
									direct	M1 to M4 DDR memories	p7			
									direct	M5 to M8 DDR memories	p8			
									direct	Pull-ups	p4			

Processor power domains
Power Rail access requiring easy soldering adaptation
Power Rail access requiring medium complexity modification
Power Rail access requiring very complex modification